



## 300kVA

### Silenced Generator

Engine Ref: CUMMINS

ALTERNATOR Ref: MECC ALTE

- Hot dip galvanised sound attenuated enclosure
- Powder coated grey raal 7035
- Bunded 600 litre base fuel tank complete with 3 way valve.
- Central lift point and forklift pockets
- Complete with rubber bumpers
- 4 pole circuit breaker with earth leakage protection
- Hardwire via copper bus bars
- Micro switch protection
- CT for genset paralleling
- External contact for autostart
- Motorised MCCB
- Deep sea 8610 genset synch panel
- Plastic coated locks/handles
- lockable canopy with single common key
- Oil extraction pump
- Battery isolator
- Oil pressure sensor
- Water temperature sensor
- Water jacket heater
- Velcb with on/off switch
- Battery charger
- Cummins water separator filter

Standby (kVA)	Prime Power (kVA)	Engine Make Type	Governor	Tank Capacity (Litre)	Fuel Consumption per hour (Litre)			dBA @ 7m	Size (mm)	Wet Weight (kg)	Control Panel
					50%	75%	100%				
330	300	CUMMINS	Electronic	600	31.95	47.93	63.90	68	L - 3900 H - 2230 W - 1200	4180	Deep Sea 8610

### Power Depots:

#### Midlands

Fairfield Park,  
Halesowen,  
B62 9JL  
Tel: 0121 559 1818

#### South East

Europa Park  
Grays  
RM20 4DB  
Tel: 0137 536 6766

#### South West

Bradley Road,  
Bristol  
BS20 7NZ  
Tel: 0117 901 2199

#### West Yorkshire

Flanshaw Way  
Wakefield,  
WF2 9PL  
Tel: 0192 497 7077

#### North East

Shadon Way  
Chester-le-Street  
DH3 2RN  
Tel: 0191 411 1200

#### Scotland

Livingston  
West Lothian  
EH54 5GG  
Tel: 01506 353 399

#### John F Hunt Fuels

Tel: 0808 175 1111

